

DATENBLATT

ADA-FLEX-06P-050-SM



BESCHREIBUNG

This adapter is designed for a comfortable connection of FFCs or FPCs with other plug connectors. It has a grid of 0.50 mm / 6-pin and a height of 0.30 mm.

A small adapter board is equipped with a FFC/FPC connector (bottom contact) and a multi-pin connector, 6-pin, pitch 1.25 mm to adapt a crimping socket for single conductors.

PROS:

- small, light & flat
- easy to handle
- no customized design for small quantities required
- customizable

TECHNICAL SPECIFICATIONS:

- side 1: FFC connector bottom, 6-pin, pitch = 0.50 mm
- side 2: 53621-0600 (compatible with 51021-0600), 6-pin, pitch 1.25 mm
- dimension: 15,0 (l) x 20,0 (w) x 1,7 (h) (in mm)
- operating temperature: -20 °C to 85 °C
- weight: 4,4 g

NOT INCLUDED IN STANDARD SCOPE OF SUPPLY: Ribbon cable of 500 mm [KAB-51021-0600-0500FK](#) with the matching number of poles, 6-pin connector, pitch = 1.25 mm. The FFC/FPC connector is designed for 0.30 mm (+/- 0.05 mm) FFCs/FPCs. The connector applies electrical contact to the FFC/FPC cable from below. You will find the suitable FFC cables with our [FFC CONFIGURATOR](#).

Further lengths are also available upon request at short notice.

BILDER



Disclaimer: In the absence of confirmation by device specification sheets, ES&S Solutions GmbH takes no responsibility for any defects that occur in equipment using any of ES&S's devices, shown in catalogs, data books, etc. Contact ES&S in order to obtain the latest device specification sheets before using any ES&S's device. ES&S reserves the right to make changes in the specifications, characteristics, data, materials, structures and other contents described herein at any time without notice in order to improve design or reliability. Contact ES&S in order to obtain the latest specification sheets before using any ES&S's device. Manufacturing locations are also subject to change without notice. Observe the following points when using any device in this publication. ES&S takes no responsibility for damage caused by improper use of the devices. ES&S's devices shall not be used for equipment that requires extremely high level of reliability, such as: -Military and space applications -Nuclear power control equipment -Medical equipment for life support